# Fluke 88V and 77 IV **Digital Multimeters**

## Versatile meters for automotive repair, field service or bench repair



#### Fluke 88V Automotive Multimeter

to help automotive professionals beat the book. This DMM has more measurement functions, troubleshooting features and accuracy to solve virtually any problems on conventional and hybrid vehicles.

#### **Features**

- Automotive test functions include dc and ac voltage, resistance and current.
- Min/Max recording for logging the highest and lowest readings over time.
- Frequency measurements for magnetic sensors and ac/dc frequency signals.
- Duty Cycle for variable duty cycle signals with selectable trigger slope and level.
- Pulse width for fuel injector on time measurements.
- Conductance testing for secondary ignition coils.
- RPM measurements for DIS and conventional ignition systems.
- Built-in thermometer.













The 77 IV Digital Multimeter has the features needed to repair most electrical and electronic problems. This meter is simple to use and has significant improvements over Fluke's original 70 Series with more measurement functions, conformance to the latest safety standards, and a much larger display that's easier to view.

- Wide 1000 V measurement range.
- Average responding at measurements.
- 0.3 % accuracy.
- 10 Amps continuous.
- Frequency and capacitance.
- Resistance and continuity.













The Fluke 88V Automotive Multimeter is designed

## For the complete diagnostics package and maximum value, pick up the 88V/A combo kit.

**ELLIKE** 

- Includes Fluke 88V Automotive Multimeter.
- TL224 Heat Resistant Silicone Test Leads.
- TP220 Removable Sharp Point Test Probes.
- AC285 Large Jaw Alligator Clips.
- TPAK Magnetic Hanger.
- 80BK-A Temperature Probe.
- RPM80 Inductive Pick-up.
- Automotive Backprobe Pins.
- Insulation Piercing Probe.
- Packaged in a durable carrying case (C800).

#### **Features**

- Large display.
- Backlight for work in dim areas.
- Min/Max to record signal fluctuations.
- Integral holster with probe holders.
- Free your hands with the optional TPAK magnetic hanger.
- Auto and Manual ranging.

## Specifications - 77 IV Digital Multimeter

| Functions   | Range                    | Best accuracy | Best resolution |
|-------------|--------------------------|---------------|-----------------|
| V dc        | 600.0 mV to 1000 V       | ± (0.3 % + 1) | 0.1 mV          |
| V ac        | 6.000 V to 1000 V        | ± (2.0 % + 2) | 1.0 mV          |
| A dc        | 60.00 mA to 10 A         | ± (1.5 % + 2) | 0.01mA          |
| A ac        | 60.00 mA to 10 A         | ± (2.5 % + 2) | 0.01 mA         |
| Resistance  | 1/1/Λ/\ 600.0 Ω to 50 MΩ | ± (0.5 % + 1) | 0.1 Ω           |
| Capacitance | 1 nF to 9,999 μF         | ± (1.2 % + 2) | 1 nF            |
| Frequency   | 99.99 Hz to 99.99 kHz    | ± (O.1 % + 1) | 0.01 Hz         |

### Recommended accessories - 77 IV Digital Multimeter











**Digital Multimeters** 

For more information, go to www.fluke.com

## Included accessories

Fluke 88V: Test leads, 9 V battery (installed), carrying case and users

Fluke 77 IV: TL75 test leads, 9 V battery (installed) and users manual.

### **Ordering information**

FLUKE-88-5 Automotive Multimeter FLUKE-88-5/A KIT Automotive Multimeter Combo Kit

FLUKE-77-4 Digital Multimeter

